

- * High Compact, High Reliability & Low Cost Sensor Controller.
- * Input NPN or PNP Selectable.(A : NPN · B : PNP)
- * Suited for Proximity Sensor or Photo Sensor.



》 C Series Sensor Controller

Outline	40×50mm (under panel type) May select and purchase Y-40 to transform for the plate form Fixed Hole 43×53mm			
Model	C-6-□□□V	C-10-□□□V	C-11-□□□V	C-12-□□□V
Figure				
Timer	Non	OFF DELAY	ON DELAY or ONE SHOT	ON DELAY+OFF DELAY
Range of Timer	0~10秒 Secretary Adjustable			
Power Suppl	110V or 220V or 380VAC±20% 50/lectable.(A : NPN · B : PNP)			
Input Method	NPN or PNP Sey			
DC Power Output	12VDC/40mA Max			

Outline	61×60mm (under panel type)		
Model	C-1	C-2	C-3
Figure			
Timer	Non	ONE SHOT or OFF DELAY or ON DELAY	Timer1 : ON DELAY Timer2 : ONE SHOT or OFF DELAY or ON DELAY
Range of Timer	0~1秒 or 0~10秒 Secretary Adjustable		
Power Supply	110V or 220VAC±20% 50/60Hz		
Input Method	NPN Input2 < AND IN >		
DC Power Output	12VDC/150mA Max		