
HAND **TACHOMETER**

TM-5000/TM-5010

- Non-contact and contact measurement using an adapter
- Measurement for hard to reach areas using the remote sensor
- 6.0~99999.9 rev/min Measuring range with multi-unit selection
- Easy to measure
- In conformance to CE



▲ TM-5000 0.1 rpm resolution



TM-5013/TM-5014

Rubber tip Surface speed wheel





 ϵ **RoHS**

TM-5010/TM-5010E A

8 items memory, MIN/MAX memory, rpm/rps unit of peripheral speed selection



TM-5000K/TM5000EK TM-5000 Kit models

TM-5010K/TM-5010EK

TM-5010 Kit models TM-5010E Kit models

All kit models includes the main unit, reflective tape, contact adapter, rubber tip, surface speed wheel, AAA batteries and carring case.

Models

[]* This item is for TM-5000EK only.

Specifications (Main unit)				
Model	TM-5000	TM-5010/5010E		
Measuring Range	6.0 - 99999.9 r/min			
Resolution	0.1 r/min	0.1 rpm/fpm,others 0.01		
Accuracy	±0.01%±1digit r/min, m/min (for other units, the conversion accuracy is ±0.05%±1digit)			
Sampling Time	1.0 - 10.0 seconds			
Display	Display : 6 o Battery alarm : Reflective light : Display unit : r/min	Display unit : r/min, r/s, m/min, cm/s [inch/s, f/min, y/min]*		
Auto Power-off	Memory display : MAX,MIN,MEM1-8 After 3 mins. from last measurement or key operation			
Data Hold Time	Measurement data: until the next data is defined			
		Memory data: same as battery life		
Measuring Method	Non-contact measurement using the main unit or with remote sensor (use with reflective tape) Contact measurement using the in-contact adapter (use with rubber tip, surface speed wheel)			
Measuring Distance	50 - 300mm (using reflective tape)			
Power Supply	4 pieces of AAA alkaline battery (continuous measurement of 20 hrs.)			
Storage Temperature	-10 - 60°C (Non-Freezing)			
Operating Temperature	5 - 40°C (Non-Freezing)			
Operating Humidity	35 - 85%RH (Non-Condensing)			
Dimension/ Weight	122(H) x 58(46)(W) x 28(D)mm	approx. 130g (including batteries)		
]* These measuring units are only available in TM-5010E model.				

Parts		
Photoelectric detector indication TM-4015 Connector for remote sensor probe The remote sensor can be used by turning the slide switch inside the battery box located at the back of this unit.	######################################	Surface speed wheel (circumference 1/10m or 1/10y) Combination of adapter with TM-5000 or TM-5010 / TM-5010E is available. For TM-5010, displayed value is 1/10m/min. For TM-5010 / TM-5010E, calculations are done internally to display the units m/min, m/sec, f/min, inch/sec and y/min, which can be read directly. In-contact adapter Contact measurement or surface speed measurement is possible using the rubber tip or the surface speed wheel in combination with TM-5000 or TM-5010 / TM-5010E. Attention! When using at high speed, be very careful that the portion being measured don't get dragged on. Photoelectric part Unit display Photoelectric detector indication Measurement display Measurement button While it is pressed, measurement is performed. Connector for remote sensor probe Measurement value MAX varbe MIN value 8-point memory data input key 8-point memory data read/clear key TM-5010 / TM-5010E